


# Surface Transformer

DUAL-FEED, 12 VOLTS 600 WATTS



Shown approx. 15% actual size.



kl\_srt60d\_spec.pdf

## DESCRIPTION

This dual-feed surface transformer converts standard 120 volt line voltage to 12 volts to provide the necessary voltage for powering a Kable Lite system. It can power lamps totaling up to 600 watts. The transformer is concealed inside a decorative housing equipped with two fast-acting secondary circuit breakers that will safely turn off the system should a short occur. Once the short has been removed the breaker can be reset.

## INSTALLATION

This product can mount to either a standard 4" square electrical box with round plaster ring or an octagon electrical box (not included). Isolating connectors (included) isolate the two power feeds from each other.

## DIMMING

Dimmable with a 1000 watt low-voltage magnetic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics). This surface transformer includes a preinstalled debuzzing dimming coil to reduce audible noise when using a low-voltage dimmer.

## FINISH

Chrome, satin nickel, black, white. Black and white finish have chrome feeds.

## COMPATIBLE RIGID STANDOFFS

The shortest rigid standoff that can be used with this surface transformer is the 5" rigid post standoff (sold separately).

## OPTIONS

This surface transformer may be plugged in with the addition of a Plug Option, a 16 foot cord with inline switch two feet from the plug (sold separately).

## REQUIRED USAGE

12 volt transformers require the use of 12 volt lamps.

## WEIGHT

20.40 lb./9.25 kg. ±

## ORDERING INFORMATION

### 700SRT60D

#### FINISH

- C CHROME
- S SATIN NICKEL
- B BLACK
- W WHITE



7400 Linder Avenue T 847.410.4400  
Skokie, Illinois 60077 F 847.410.4500

[www.techlighting.com](http://www.techlighting.com)

700SRT60D \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

